



ME200BK

LPA140D



LPA120DD

REMOTELINK™ Line Powered Amplifiers

- Compact amps powered by SKY™ digital receiver
- Fully screened with F-Type connectors and LED indicator
- Watch and change channels in 2 or 4 extra rooms
- Compatible with ME100 and ME200 RemoteLink IR sensor

PRODUCT RANGE

- LPA120D - 2 room line powered amp
- LPA140D - 4 room line powered amp
- ME100 - RemoteLink IR sensor (black or silver)
- ME200- RemoteLink IR sensor (black or silver)

TECHNICAL SPECIFICATION

	LPA120D	LPA140D
No. of Inputs	1	1
No. of Outputs	2	4
Frequency Range	88-862MHz	88-862MHz
Gain	7dB	6dB
Noise Max	<3.5dB	<3.5dB
Max. Output*	78dB μ V	78dB μ V
Isolation Between Outputs	>15dB	>15dB
Return Path Frequency	5-30MHz	
Impedance	75 Ω	
Power Supply from Sat. receiver	9V DC >75mA (inc. R-L Eyes)	
Power Supply via 3.5mm Jack external supply	12V DC >75mA (inc. R-L Eyes)	
* DIN 45004B 3 carriers, IMD ₃ - 60dB		